

SPECIFICATION SHEET

JFW MODEL 50P-2142

4 CHANNEL USB CONTROLLED SOLID STATE PROGRAMMABLE ATTENUATOR

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	30-3000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-63.5 dB in 0.5 dB steps
Attenuation Steps	0.5, 1, 2, 4, 8, 16 and 32 dB
VSWR	1.8:1 maximum 30-800 MHz 1.5:1 maximum 800-3000 MHz
Attenuation Accuracy (guaranteed monotonic)	± 0.3 dB 0.5-7.5 dB ± 0.5 dB or 2% 8.0-63.5 dB (whichever is greater)
Insertion Loss	4.0 dB maximum 2.2 dB typical @ 30 MHz 3.5 dB typical @ 3000 MHz
RF Input Power	+27 dBm (operating) +33 dBm (no damage)
Switching Speed	4 microseconds maximum (after command is received and processed) (1 millisecond typical processing time)
DC Supply	+5 Vdc @ 400mA typical (Powered via USB)
Control	USB control (CDC-ACM Serial Device)
Test Software (Microsoft .NET 4.0+) (Windows Vista or greater)	The included JFW software allows control of multiple USB devices. Unit is also compatible with Python, C#, PuTTY (any development tool with COM Port interfacing).
DC Connector	USB-C 2 meter USB A Male to USB-C Cable Included
RF Connector	SMA female
Operating Temperature Range	-40°C to +85°C
Physical Size	See outline drawings 092-9250

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	07/01/2024		TRS 07/01/2024				