## SPECIFICATION SHEET

## JFW MODEL 50PD-922

## 2 WAY RESISTIVE POWER DIVIDER

JFW Industries, Inc. Phone: 317-887-1340 sales@jfwindustries.com www.jfwindustries.com

Frequency Range DC-18 GHz

Impedance 50 Ohms nominal

VSWR 1.4:1 maximum

1.1:1 typical @ 6 GHz 1.3:1 typical @ 18 GHz

Insertion Loss 7.8 dB maximum

6.0 dB typical @ DC

7.0 dB typical @ 18 GHz

Amplitude Tracking ± 0.5 dB maximum

Phase Tracking ± 4° typical

(output to output)

RF Input Power 1 Watt average @ +25°C

Operating Temperature Range -40°C to +85°C

RF Connector SMA female

Physical Size See outline drawing 092-10066

ECR/ECN # DATE	REV APPR / DATE	ECR/ECN # DATE	REV APPR / DATE
06/01/2023	TRS 06/01/2023		

Page 1 of 1 JFW FORM E-7-F REV F